



# Battery Maintenance Tool

## Major Benefits: -

Battery Deep discharge recovery

Battery Desulfation

Battery Booster

## For the following batteries and applications



## TECHNICAL DATA

Main Voltage	1- 230v
Mains Frequency	50/60 Hz
AC input current in A effectiv	2,3 A
Mains fuse	16,0 A
Nominal Power	315,0 W
Power Factor (pf)	0,62
Duty Cycle	100,0 %
Nomil output voltage	12,0 V
Output Voltage Range	2 -16,8V
Charging current / output current nominal	20,0 A
Dinension / I	245,0 mm
Dimension / h	155,0 mm
Weight	1,9 kg
Ambient Temperature Range	-20C / +40C
Maximum Relative Humidity	85,0
Maximum Altitude above Sea level	2000M
Protection class	40,0
Test symbol	CE

## FUNCTIONS

### SELECTIVA 1KW

- Up to 96% efficiency
- LED charging status indication
- Compact, lightweight design
- Modular design for simple servicing as well as convenient upgrading and retrofitting
- Based on Active Inverter Technology

### Fronius India Private Limited

Plot no. BG 71/2/B, Pimpri Industrial Area, MIDC ,Bhosari, Pune – 411026, Maharashtra, India

Mob:- +91 73910 95707 | 73910 95734, Email ID:-perfect.charging.in@fronius.com